

## Customize format of z30-item-sequence in missing-items-report

- **Article Type:** General
  - **Product:** Aleph
  - **Product Version:** 20
- 

### Problem Symptoms:

- \* need to customize printout missing-items-report (from service Missing Items Report (p-ret-item-02))
- \* need value ./z30-item-sequence without decimal point and zero
- \* printout currently has:  
1.0 or 2.0 or 3.0
- \* needed is this:  
1 or 2 or 3

### Cause:

In xxx01/form\_hrv/global.trn, the following translate mechanism is configured for the z30-item-sequence:

z30-item-sequence ITEM-SEQ S

### Resolution:

- \* None of the available translate mechanisms (see document attached to KB Item 8192-7447) produces 1 or 2 or 3.
- \* Solve problem via XSL:

1. Modify print template as follows:

missing-items-report.xsl

```
..  
<xsl:template name="section-02">  
<xsl:param name="header"/>  
<xsl:if test="$header!="">  
<xsl:call-template name="start-grid"/>  
</xsl:if>  
<xsl:call-template name="table-start-row"/>  
<xsl:call-template name="display-grid-gen">  
<xsl:with-param name="label" select="Inventory"/>  
<xsl:with-param name="value" select="./inventory"/>  
<xsl:with-param name="header" select="$header"/>  
</xsl:call-template>  
<xsl:call-template name="display-grid-gen">  
<xsl:with-param name="label" select="Doc Number"/>  
<xsl:with-param name="value" select="./z30-doc-number"/>  
<xsl:with-param name="header" select="$header"/>  
</xsl:call-template>  
<xsl:call-template name="display-grid-gen">  
<xsl:with-param name="label" select="Item Sequence"/>
```

```
<xsl:with-param name="value" select="substring-before(z30-item-sequence, '.')"/> << change like this
<xsl:with-param name="header" select="$header"/>
</xsl:call-template>
```

..

2. After making the change, create new print template package via util i/6.

**Category:** Printing (500)

---

- **Article last edited:** 10/8/2013