

---

## file-20: "Can not update/delete. No match found."

- **Article Type:** General
  - **Product:** Aleph
  - **Product Version:** 20, 21, 22, 23
- 

### Description

The following messages appear in the file-20 (Patron Loader):

1.

```
Error (b_file_20_chk_edit_record) : Errors in Z304. Record No 000540  
Can not update/delete. No match found.
```

OR:

2.

```
Error (b_file_20_chk_edit_record) : Errors in Z305. Record No 000002  
Can not update/delete. No match found.
```

### Resolution

The USER-REC-ACTION, ADDR-REC-ACTION, etc., (the first byte in each segment) is "U" (Update) when the patron does not exist.

\* Unless it is certain that the patron exists, the xxxx-REC-ACTION needs to be "A" (Add) rather than "U" Update.

\* For "A" the program checks to see if the patron exists. If so, it changes the action to "U"; if not, it changes it to "I".

OR, In the case of the z305 (#2), if XML input is being used, with just one or two fields you want to update, in addition to those fields you must include at least:

the <match-id-type>,  
the <match-id>, and  
the <z305-sub-library>\*.

Otherwise, the program won't be able to find the z305 you want to match on.

\* Note: the z305\_sub\_library is commonly the ADM library code (such as USM50).

- **Article last edited:** 30-Sep-2016