
p_file_20: "check_z303 routine failed"; "Z303-ILL-LIBRARY is not valid"

- **Article Type:** General
 - **Product:** Aleph
 - **Product Version:** 20
-

Description:

The \$data_scratch/p_file_20_report has "check_z303 routine failed" messages and the \$alephe_scratch p_file_20 log has:

Error 0201 : Z303-ILL-LIBRARY is not valid

Resolution:

The check_z303 program checks to see if there is an Z700 (ILL partner) record for the ILL-LIBRARY in the \$pw_library. If not, or if the Z700-UNIT value is not "Y", it returns this 0201 error.

If you do not use ILL, the USER-REC-ILL-LIBRARY must be blank.

Additional Information

Article 000040326 [Oracle error: update_cursor z700; ... table or view does not exist](#) is relevant.

In one case the site asked their database services people how they put the blanks in the spaces where ILL-LIBRARY used to be and it turns out they didn't use blanks, but another "invisible" value of Datatel. When they re-did the PLIF files to deliberately use blanks, the files loaded properly.

Category: Circulation

- **Article last edited:** 10/8/2013