
How to setup a logical base for the OPAC?

- **Product:** Aleph
 - **Product Version:** 20, 21, 22, 23
 - **Relevant for Installation Type:** Dedicated-Direct, Direct, Local
-

Question

How to setup a logical base for the OPAC?

Answer

A logical base is a predefined set of records based on specific criteria. It is useful for searching in WEB OPAC because it limits a user's search to be within a predefined set.

The base has to be added to the following tables:

(1) \$alephe_tab/tab_base.lng

Example:

```
!           1           2           3           4           5           6           7           8           9
!!!!!!!!!!!!!!!!!!!!!!!!!!!!-!-!!!!!!!!!!!!!!!!!!!!!!!!!!!!-!!!!!!-!!!!!!-!!!!!!-!!!!!!-!!!!!!-!-!!!!!!!!!!!!>

WID           Main Library           USM01           USM01 Y wsl=wid
```

(2) \$alephe_root/www_f_lng/base-list

Example:

```
<td class=text3>
  
  <a href="&server_f?func=find-b-0&local_base=WID">
  Main Library </a>
</td>
```

-
- **Article last edited:** 19-Sept-2016